

A Series 10 and 16 Amps 600 VAC

3 or 4 Contacts + Ground: 10A
10, 16 & 32 Contacts + Ground: 16A

Install to
 Matching Series
 Hood/Base

3 or 4 (600V)	10	16	32

Screw Terminal Inserts		3 or 4 + G	10 + G	16 + G	32 + G
	Male – Pins 20-14 AWG (0.5-2.5 mm ²)	MS203A or MS204A (16 AWG max)	MS210A	MS216A	MS216A + MS232A
	Female – Sleeves 20-14 AWG (0.5-2.5 mm ²)	FS103A or FS104A (16 AWG max)	FS110A	FS116A	FS116A + FS132A



Use small blade screwdriver to push in wire entry tab for easy contact removal.

Crimp Terminal Inserts	
	Male Insert (Order contacts below)
	Female Insert (Order contacts below)

10 + G	16 + G	32 + G
MC410A	MC416A	MC416A + MC432A
FC310A	FC316A	FC316A + FC332A



Contacts Selection			
Crimp Contacts	Wire AWG (mm ²)	Identification	
	20 AWG (0.5 mm ²)	No Groove	
	18 AWG (0.75-1 mm ²)	1 Groove	
	16 AWG (1.5 mm ²)	2 Grooves	
	14 AWG (2.5 mm ²)	3 Grooves	
	12 AWG (4.0 mm ²)	No Groove	

For all Crimp Terminal “A” Inserts

Female	Male
FP2000	MP2000
FP1800	MP1800
FP1600	MP1600
FP1400	MP1400
FP1200	MP1200

Adapter Mount Frames allow “open” wiring inside closed panel enclosure. They also allow Inserts to be assembled as a separable Terminal Block device.

DIN Rail Adapter Mount Frames	
	150mm long, with base for snapping onto DIN rail









For all Inserts

10 + G	16 + G
AMF115	AMF125





A Series 10 and 16 Amps 600 VAC



Number of Contacts + Ground Connection

		Number of Contacts + Ground Connection								
		3 or 4 (600V)	10	16	32					
Single Lever	Double Lever	Housing	NPT Entry	Lever Locking Type						
				Single	Single	Single	Double			
Bases – Standard Mount		 	Panel Base	PB303A(P) _S PB403A PB503A(P) _S	PB310A PB410A	PB316A PB416A	PB132A			
 	Box Base (no Cover)							1 X 3/8" 1 X 1/2" 1 X 3/4" 1 X 1" 2 X 1/2" 2 X 3/4" 2 X 1"	BB403A(P) _S BB410A BB416A BB510A BB516A	BB032A BB832A BB132A BB132A100
Hoods – Standard Mount		Plastic body – "A" 3-16 Series standard Hoods include Gaskets: Bases and Special Hoods do not.								
 	Side Entry	1 X 3/8" 1 X 1/2" 1 X 3/4" 1 X 1"	SH603A(P) _S TH803A(P) _S	SH610A* SH710A TH810A* TH910A	SH616A* SH716A TH816A* TH916A	SH032A SH132A TH232A TH332A				
							 	Top Entry	1 X 3/8" 1 X 1/2" 1 X 3/4" 1 X 1"	CH803A(P) _S
Coupler Hoods – In-line		Top Entry	1 X 3/8" 1 X 1/2"	CH803A(P) _S	CH810A CH816A					

For In-line, Portable or Special Service Connections
Coupler Hoods mate to Standard Hoods ONLY.

Lever Hoods – Rev. Lock	
	Side Entry w/Lever(s) 1 X 3/4" 1 X 1"
	Top Entry w/Lever(s) 1 X 3/4" 1 X 1"

Reverse Locking
Lever Hoods mate to Post Bases ONLY.

Bases – with Access Cover	
	Panel Base+ Posts w/Cover 1 X 3/4" 1 X 1" 2 X 3/4" 2 X 1"
	Box Base+ Posts w/Cover 1 X 3/4" 1 X 1" 2 X 3/4" 2 X 1"

Post Bases accept Lever Hoods ONLY.

*Available in Standard or LOW Profile "L" configurations (add suffix L).
 S (P) indicates glass-filled thermoplastic construction, light grey colour (add suffix P).
 (PB) indicates glass filled thermoplastic construction, black colour (add suffix PB). Minimum quantity. Purchase may be required.

POSE-KON™

B
A
S
E
T
O
H
O
O
D
H
O
O
D
T
O
C
O
U
P
L
E
R