

Guide de référence - Combinaisons de fils

À moins d'indications contraires, toutes les combinaisons indiquées sont pour des connexions cuivre à cuivre seulement.

N° de modèle	Nbre de cond.	AWG	+ Nbre de cond.	AWG	+ Nbre de cond.	AWG
1SH	1	18	1	14	-	-
1SH	1	18	2	14	-	-
1SH	1	18	3	14	-	-
1SH	2	18	-	-	-	-
1SH	2	18	1	14	-	-
1SH	2	18	2	14	-	-
1SH	3	18	-	-	-	-
1SH	3	18	1	14	-	-
1SH	4	18	-	-	-	-
1SH	5	18	-	-	-	-
1SH	6	18	-	-	-	-
1SH	7	18	-	-	-	-
1SH	8	18	-	-	-	-
1SH	1	16	1	14	-	-
1SH	2	16	-	-	-	-
1SH	2	16	1	14	-	-
1SH	3	16	-	-	-	-
1SH	4	16	-	-	-	-
1SH	5	16	-	-	-	-
1SH	2	14	-	-	-	-
1SH	3	14	-	-	-	-
1SH	2	12	-	-	-	-
10401	1	18	2	16	-	-
10401	1	18	1	14	-	-
10401	2	18	-	-	-	-
10401	2	18	1	16	-	-
10401	3	18	-	-	-	-
10401	4	18	-	-	-	-
10401	2	16	-	-	-	-
10405	1	18	1	16	-	-
10405	1	18	2	16	-	-
10405	1	18	1	14	-	-
10405	2	18	-	-	-	-
10405	2	18	1	16	-	-
10405	2	18	2	16	-	-
10405	2	18	1	14	-	-
10405	3	18	-	-	-	-
10405	3	18	1	16	-	-
10405	4	18	-	-	-	-
10405	1	16	1	14	-	-
10405	2	16	-	-	-	-
10405	3	16	-	-	-	-
10407	1	18	1	16	-	-
10407	1	18	2	16	-	-

N° de modèle	Nbre de cond.	AWG	+ Nbre de cond.	AWG	+ Nbre de cond.	AWG
10407	1	18	3	16	-	-
10407	1	18	1	14	-	-
10407	1	18	2	14	-	-
10407	1	18	1	12	-	-
10407	2	18	-	-	-	-
10407	2	18	1	16	-	-
10407	2	18	1	14	-	-
10407	3	18	-	-	-	-
10407	3	18	1	16	-	-
10407	3	18	1	14	-	-
10407	4	18	-	-	-	-
10407	5	18	-	-	-	-
10407	1	16	1	14	-	-
10407	1	16	1	12	-	-
10407	2	16	1	14	-	-
10407	2	16	-	-	-	-
10407	3	16	-	-	-	-
10407	4	16	-	-	-	-
10407	2	14	-	-	-	-
2SH	1	16	2	14	-	-
2SH	2	16	1	14	-	-
2SH	2	16	2	14	-	-
2SH	3	16	1	14	-	-
2SH	2	10	-	-	-	-
30	1	22	1	20	-	-
30	1	22	1	20	1	18
30	1	22	1	20	1	16
30	1	22	3	20	-	-
30	1	22	4	20	-	-
30	1	22	1	18	-	-
30	1	22	2	18	-	-
30	1	22	3	18	-	-
30	1	22	4	18	-	-
30	1	22	1	16	-	-
30	1	22	2	16	-	-
30	1	22	1	14	-	-
30	2	22	1	20	-	-
30	2	22	2	20	-	-
30	2	22	3	20	-	-
30	2	22	4	20	-	-
30	2	22	1	18	-	-
30	2	22	2	18	-	-
30	2	22	3	18	-	-
30	2	22	1	16	-	-
30	2	22	2	16	-	-
30	2	22	1	14	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	+ Nbre de cond.		+ Nbre de cond.	
		AWG	AWG	AWG	AWG
30	3	22	-	-	-
30	3	22	1	20	-
30	3	22	2	20	-
30	3	22	1	18	-
30	3	22	1	16	-
30	3	22	2	16	-
30	3	22	1	14	-
30	4	22	-	-	-
30	4	22	1	20	-
30	4	22	1	18	-
30	4	22	1	16	-
30	4	22	1	14	-
30	5	22	-	-	-
30	5	22	1	18	-
30	1	20	1	18	-
30	1	20	2	18	-
30	1	20	3	18	-
30	1	20	1	16	-
30	1	20	2	16	-
30	1	20	1	14	-
30	2	20	-	-	-
30	2	20	1	18	-
30	2	20	3	18	-
30	2	20	1	16	-
30	2	20	2	16	-
30	2	20	1	14	-
30	3	20	-	-	-
30	3	20	1	18	-
30	3	20	1	16	-
30	3	20	1	14	-
30	4	20	-	-	-
30	4	20	1	18	-
30	4	20	1	16	-
30	5	20	-	-	-
30	1	18	1	16	-
30	1	18	2	16	-
30	1	18	1	14	-
30	2	18	-	-	-
30	3	18	-	-	-
30	4	18	-	-	-
30	1	16	1	14	-
30	2	16	-	-	-
30	3	16	-	-	-
31	1	18	1	16	-
31	1	18	2	16	-
31	1	18	3	16	-
31	1	18	1	14	-

N° de modèle	Nbre de cond.	+ Nbre de cond.		+ Nbre de cond.	
		AWG	AWG	AWG	AWG
31	1	18	2	14	-
31	2	18	-	-	-
31	2	18	1	16	-
31	2	18	2	16	-
31	2	18	1	14	-
31	3	18	-	-	-
31	3	18	1	16	-
31	3	18	2	16	-
31	3	18	1	14	-
31	4	18	-	-	-
31	4	18	1	16	-
31	5	18	-	-	-
31	1	16	1	14	-
31	2	16	-	-	-
31	2	16	1	14	-
31	3	16	-	-	-
31	4	16	-	-	-
31	2	14	-	-	-
33	1	18	1	14	-
33	1	18	2	14	-
33	1	18	3	14	-
33	1	18	1	12	-
33	2	18	1	16	-
33	2	18	2	16	-
33	2	18	3	16	-
33	2	18	4	16	-
33	2	18	1	14	-
33	2	18	2	14	-
33	2	18	1	12	-
33	3	18	1	16	-
33	3	18	2	16	-
33	3	18	1	14	-
33	3	18	2	14	-
33	3	18	1	12	-
33	4	18	1	16	-
33	4	18	2	16	-
33	4	18	1	14	-
33	4	18	1	12	-
33	5	18	-	-	-
33	1	16	1	14	-
33	1	16	2	14	-
33	1	16	3	14	-
33	1	16	1	12	-
33	2	16	1	14	-
33	2	16	2	14	-
33	2	16	1	12	-
33	3	16	-	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
33	3	16	1	14	-	-
33	3	16	2	14	-	-
33	3	16	1	12	-	-
33	4	16	-	-	-	-
33	4	16	1	14	-	-
33	5	16	-	-	-	-
33	1	14	1	12	-	-
33	2	14	-	-	-	-
33	2	14	1	12	-	-
33	3	14	-	-	-	-
33	4	14	-	-	-	-
33	2	12	-	-	-	-
35	1	18	4	14	-	-
35	1	18	5	14	-	-
35	1	18	6	14	-	-
35	1	18	2	12	-	-
35	1	18	3	12	-	-
35	1	18	1	10	-	-
35	1	18	2	10	-	-
35	1	18	3	10	-	-
35	2	18	4	16	-	-
35	2	18	4	14	-	-
35	2	18	6	14	-	-
35	2	18	2	12	-	-
35	2	18	3	12	-	-
35	2	18	1	10	-	-
35	2	18	2	10	-	-
35	3	18	4	14	-	-
35	3	18	2	12	-	-
35	3	18	3	12	-	-
35	3	18	1	10	-	-
35	3	18	2	10	-	-
35	4	18	2	12	-	-
35	4	18	1	10	-	-
35	4	18	2	10	-	-
35	5	18	2	12	-	-
35	5	18	1	10	-	-
35	6	18	1	10	-	-
35	6	18	1	18	1	12
35	1	16	4	14	-	-
35	1	16	5	14	-	-
35	1	16	6	14	-	-
35	1	16	2	12	-	-
35	1	16	3	12	-	-
35	1	16	1	10	-	-
35	1	16	2	10	-	-
35	2	16	4	14	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
35	1	12	3	10	-	-
35	1	12	1	8	-	-
35	2	12	-	-	-	-
35	2	12	1	10	-	-
35	2	12	2	10	-	-
35	2	12	1	8	-	-
35	3	12	-	-	-	-
35	3	12	1	10	-	-
35	3	12	1	8	-	-
35	4	12	-	-	-	-
35	4	12	1	10	-	-
35	5	12	-	-	-	-
35	1	10	1	8	-	-
35	2	10	-	-	-	-
35	2	10	1	8	-	-
35	3	10	-	-	-	-
35	4	10	-	-	-	-
35	2	8	-	-	-	-
329	1	22	1	20	-	-
329	1	22	2	20	-	-
329	1	22	3	20	-	-
329	1	22	1	20	1	18
329	1	22	1	20	1	16
329	1	22	1	18	-	-
329	1	22	2	18	-	-
329	1	22	1	16	-	-
329	2	22	1	20	-	-
329	2	22	2	20	-	-
329	2	22	3	20	-	-
329	2	22	1	18	-	-
329	2	22	1	16	-	-
329	3	22	-	-	-	-
329	3	22	1	20	-	-
329	3	22	2	20	-	-
329	3	22	1	18	-	-
329	4	22	-	-	-	-
329	4	22	1	20	-	-
329	4	22	1	18	-	-
329	5	22	-	-	-	-
329	1	20	1	18	-	-
329	1	20	2	18	-	-
329	1	20	1	16	-	-
329	2	20	-	-	-	-
329	2	20	1	18	-	-
329	3	20	-	-	-	-
329	4	20	-	-	-	-
329	1	18	1	16	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
333	1	18	2	12	-	-
333	2	18	-	-	-	-
333	2	18	2	16	-	-
333	2	18	3	16	-	-
333	2	18	4	16	-	-
333	2	18	1	14	-	-
333	2	18	2	14	-	-
333	2	18	1	12	-	-
333	3	18	2	16	-	-
333	3	18	1	14	-	-
333	3	18	2	14	-	-
333	3	18	1	12	-	-
333	4	18	2	16	-	-
333	4	18	1	14	-	-
333	5	18	-	-	-	-
333	6	18	-	-	-	-
333	1	16	2	14	-	-
333	1	16	3	14	-	-
333	1	16	1	12	-	-
333	1	16	2	12	-	-
333	2	16	1	14	-	-
333	2	16	2	14	-	-
333	2	16	1	12	-	-
333	2	16	2	12	-	-
333	3	16	-	-	-	-
333	3	16	1	14	-	-
333	3	16	2	14	-	-
333	3	16	1	12	-	-
333	4	16	-	-	-	-
333	4	16	1	14	-	-
333	5	16	-	-	-	-
333	1	14	1	12	-	-
333	1	14	2	12	-	-
333	1	14	1	10	-	-
333	2	14	-	-	-	-
333	2	14	1	12	-	-
333	2	14	1	10	-	-
333	3	14	-	-	-	-
333	4	14	-	-	-	-
333	1	12	1	10	-	-
333	2	12	-	-	-	-
335	1	22	2	18	-	-
335	2	22	2	16	-	-
335	2	22	3	16	-	-
335	3	22	1	16	-	-
335	4	22	1	16	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
335	1	20	2	18	-	-
335	1	20	3	18	-	-
335	1	20	4	18	-	-
335	2	20	2	18	-	-
335	2	20	3	18	-	-
335	2	20	1	16	-	-
335	2	20	2	16	-	-
335	2	20	3	16	-	-
335	3	20	1	18	-	-
335	3	20	2	18	-	-
335	3	20	1	16	-	-
335	4	20	-	-	-	-
335	4	20	1	18	-	-
335	4	20	1	16	-	-
335	5	20	-	-	-	-
335	1	18	2	16	-	-
335	1	18	3	16	-	-
335	1	18	4	16	-	-
335	1	18	5	16	-	-
335	1	18	2	14	-	-
335	1	18	3	14	-	-
335	1	18	4	14	-	-
335	1	18	5	14	-	-
335	1	18	1	12	-	-
335	1	18	2	12	-	-
335	1	18	3	12	-	-
335	2	18	1	16	-	-
335	2	18	2	16	-	-
335	2	18	3	16	-	-
335	2	18	4	16	-	-
335	2	18	1	14	-	-
335	2	18	2	14	-	-
335	2	18	3	14	-	-
335	2	18	4	14	-	-
335	2	18	1	12	-	-
335	2	18	2	12	-	-
335	2	18	3	12	-	-
335	3	18	-	-	-	-
335	3	18	1	16	-	-
335	3	18	2	16	-	-
335	3	18	3	16	-	-
335	3	18	1	14	-	-
335	3	18	2	14	-	-
335	3	18	3	14	-	-
335	3	18	1	12	-	-
335	3	18	2	12	-	-
335	3	18	3	12	-	-
335	4	18	-	-	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
335	4	18	1	16	-	-
335	4	18	2	16	-	-
335	4	18	1	14	-	-
335	4	18	2	14	-	-
335	4	18	1	12	-	-
335	4	18	2	12	-	-
335	5	18	-	-	-	-
335	5	18	1	12	-	-
335	5	18	2	12	-	-
335	6	18	-	-	-	-
335	1	16	2	14	-	-
335	1	16	3	14	-	-
335	1	16	4	14	-	-
335	1	16	2	12	-	-
335	1	16	3	12	-	-
335	1	16	4	12	-	-
335	1	16	2	10	-	-
335	2	16	-	-	-	-
335	2	16	1	14	-	-
335	2	16	2	14	-	-
335	2	16	3	14	-	-
335	2	16	1	12	-	-
335	2	16	2	12	-	-
335	2	16	3	12	-	-
335	2	16	1	10	-	-
335	2	16	2	10	-	-
335	3	16	-	-	-	-
335	3	16	1	14	-	-
335	3	16	2	14	-	-
335	3	16	3	14	-	-
335	3	16	1	12	-	-
335	3	16	2	12	-	-
335	3	16	3	12	-	-
335	4	16	-	-	-	-
335	4	16	1	14	-	-
335	4	16	1	12	-	-
335	4	16	2	12	-	-
335	5	16	-	-	-	-
335	5	16	2	12	-	-
335	6	16	-	-	-	-
335	1	14	1	12	-	-
335	1	14	2	12	-	-
335	1	14	3	12	-	-
335	1	14	4	12	-	-
335	1	14	1	10	-	-
335	1	14	2	10	-	-
335	2	14	-	-	-	-
335	2	14	1	12	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
335	2	14	2	12	-	-
335	2	14	3	12	-	-
335	2	14	1	10	-	-
335	2	14	2	10	-	-
335	3	14	-	-	-	-
335	3	14	1	12	-	-
335	3	14	2	12	-	-
335	3	14	1	10	-	-
335	4	14	-	-	-	-
335	4	14	1	12	-	-
335	4	14	2	12	-	-
335	5	14	-	-	-	-
335	5	14	1	12	-	-
335	5	14	1	10	-	-
335	1	12	1	10	-	-
335	1	12	2	10	-	-
335	2	12	-	-	-	-
335	2	12	1	10	-	-
335	3	12	-	-	-	-
335	3	12	1	10	-	-
335	4	12	-	-	-	-
335	3	10	-	-	-	-
Cuivre-cuivre						
63	1	18	1	14	-	-
63	1	18	2	14	-	-
63	1	18	3	14	-	-
63	1	18	1	12	-	-
63	1	18	2	12	-	-
63	2	18	1	16	-	-
63	2	18	2	16	-	-
63	2	18	3	16	-	-
63	2	18	1	14	-	-
63	2	18	2	14	-	-
63	2	18	1	12	-	-
63	3	18	1	16	-	-
63	3	18	2	16	-	-
63	3	18	1	14	-	-
63	3	18	2	14	-	-
63	3	18	1	12	-	-
63	4	18	1	16	-	-
63	4	18	2	16	-	-
63	4	18	1	14	-	-
63	5	18	-	-	-	-
63	6	18	-	-	-	-
63	1	16	1	14	-	-
63	1	16	2	14	-	-
63	1	16	3	14	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
63	1	16	1	12	-	-
63	1	16	2	12	-	-
63	2	16	1	14	-	-
63	2	16	2	14	-	-
63	2	16	1	12	-	-
63	3	16	-	-	-	-
63	3	16	1	14	-	-
63	3	16	1	12	-	-
63	4	16	-	-	-	-
63	5	16	-	-	-	-
63	1	14	1	12	-	-
63	1	14	1	10	-	-
63	2	14	-	-	-	-
63	2	14	1	12	-	-
63	3	14	-	-	-	-
63	4	14	-	-	-	-
63	2	12	-	-	-	-
Cuivre-aluminium						
63	1	18	1	12	-	-
63	2	18	1	12	-	-
63	3	18	1	12	-	-
63	1	16	1	12	-	-
63	2	16	1	12	-	-
63	3	16	1	12	-	-
63	1	14	1	12	-	-
63	2	14*	1	12	-	-
63	1	12*	1	12	-	-
Aluminium-aluminium						
63	2	12	-	-	-	-
Cuivre-cuivre						
65	1	18	4	14	-	-
65	1	18	5	14	-	-
65	1	18	6	14	-	-
65	1	18	2	12	-	-
65	1	18	3	12	-	-
65	1	18	1	10	-	-
65	1	18	2	10	-	-
65	2	18	4	16	-	-
65	2	18	4	14	-	-
65	2	18	2	12	-	-
65	2	18	3	12	-	-
65	2	18	1	10	-	-
65	2	18	2	10	-	-
65	3	18	4	14	-	-
65	3	18	2	12	-	-

* Solide seulement

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
65	3	18	3	12	-	-
65	3	18	1	10	-	-
65	3	18	2	10	-	-
65	4	18	2	12	-	-
65	4	18	1	10	-	-
65	4	18	2	10	-	-
65	5	18	2	12	-	-
65	5	18	1	10	-	-
65	6	18	1	10	-	-
65	1	16	4	14	-	-
65	1	16	5	14	-	-
65	1	16	6	14	-	-
65	1	16	2	12	-	-
65	1	16	3	12	-	-
65	1	16	1	10	-	-
65	1	16	2	10	-	-
65	2	16	4	14	-	-
65	2	16	2	12	-	-
65	2	16	3	12	-	-
65	2	16	1	10	-	-
65	2	16	2	10	-	-
65	2	16	2	12	-	-
65	2	16	1	10	-	-
65	2	16	2	12	-	-
65	2	16	1	10	-	-
65	3	16	4	14	-	-
65	3	16	2	12	-	-
65	3	16	3	12	-	-
65	3	16	1	10	-	-
65	4	16	2	12	-	-
65	4	16	1	10	-	-
65	5	16	-	-	-	-
65	5	16	2	12	-	-
65	5	16	1	10	-	-
65	6	16	-	-	-	-
65	6	16	1	10	-	-
65	7	16	-	-	-	-
65	1	14	1	12	-	-
65	1	14	2	12	-	-
65	1	14	3	12	-	-
65	1	14	1	10	-	-
65	1	14	2	10	-	-
65	2	14	-	-	-	-
65	2	14	1	12	-	-
65	2	14	2	12	-	-
65	2	14	1	10	-	-
65	3	14	-	-	-	-
65	3	14	1	12	-	-
65	3	14	2	12	-	-
65	3	14	1	10	-	-
65	4	14	-	-	-	-
65	4	14	1	12	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
65	3	12	-	-	-	-
65	4	12	-	-	-	-
65	2	10	-	-	-	-
739	1	14	3	12	-	-
739	1	14	2	10	-	-
739	1	14	3	10	-	-
739	1	14	2	8	-	-
739	2	14	2	12	-	-
739	2	14	3	12	-	-
739	2	14	2	10	-	-
739	2	14	3	10	-	-
739	2	14	2	8	-	-
739	3	14	2	12	-	-
739	3	14	3	12	-	-
739	3	14	1	10	-	-
739	3	14	2	10	-	-
739	3	14	3	10	-	-
739	3	14	2	8	-	-
739	3	14	2	12	-	-
739	4	14	1	10	-	-
739	4	14	2	10	-	-
739	4	14	2	8	-	-
739	5	14	-	-	-	-
739	5	14	1	10	-	-
739	6	14	-	-	-	-
739	1	12	2	10	-	-
739	1	12	4	10	-	-
739	1	12	2	8	-	-
739	1	12	1	6	-	-
739	2	12	1	10	-	-
739	2	12	2	10	-	-
739	2	12	2	8	-	-
739	2	12	1	6	-	-
739	3	12	-	-	-	-
739	3	12	1	10	-	-
739	3	12	2	10	-	-
739	4	12	-	-	-	-
739	4	12	1	10	-	-
739	5	12	-	-	-	-
739	6	12	-	-	-	-
739	1	10	1	8	-	-
739	1	10	2	8	-	-
739	1	10	1	6	-	-
739	2	10	-	-	-	-
739	2	10	1	8	-	-
739	2	10	1	6	-	-
739	3	10	-	-	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
739	3	10	1	8	-	-
739	4	10	-	-	-	-
739	5	10	-	-	-	-
739	1	8	1	6	-	-
739	2	8	-	-	-	-
739	3	8	-	-	-	-
739	2	6	-	-	-	-
822	1	22	2	20	-	-
822	1	22	3	20	-	-
822	1	22	4	20	-	-
822	1	22	2	18	-	-
822	1	22	3	18	-	-
822	1	22	4	18	-	-
822	2	22	1	20	-	-
822	2	22	2	20	-	-
822	2	22	3	20	-	-
822	2	22	1	18	-	-
822	2	22	2	18	-	-
822	2	22	3	18	-	-
822	2	22	1	16	-	-
822	2	22	3	16	-	-
822	3	22	1	20	-	-
822	3	22	2	20	-	-
822	3	22	1	18	-	-
822	3	22	2	18	-	-
822	3	22	1	16	-	-
822	4	22	-	-	-	-
822	4	22	1	20	-	-
822	4	22	1	18	-	-
822	4	22	1	16	-	-
822	5	22	-	-	-	-
822	1	20	2	18	-	-
822	1	20	3	18	-	-
822	1	20	4	18	-	-
822	2	20	1	18	-	-
822	2	20	2	18	-	-
822	2	20	3	18	-	-
822	2	20	1	16	-	-
822	2	20	3	16	-	-
822	3	20	-	-	-	-
822	3	20	1	18	-	-
822	3	20	2	18	-	-
822	3	20	1	16	-	-
822	4	20	-	-	-	-
822	4	20	1	18	-	-
822	4	20	1	16	-	-
822	5	20	-	-	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
822	1	18	2	16	-	-
822	1	18	3	16	-	-
822	1	18	4	16	-	-
822	1	18	5	16	-	-
822	1	18	2	14	-	-
822	1	18	1	12	-	-
822	1	18	2	12	-	-
822	1	18	3	12	-	-
822	2	18	-	-	-	-
822	2	18	1	16	-	-
822	2	18	2	16	-	-
822	2	18	3	16	-	-
822	2	18	4	16	-	-
822	2	18	1	14	-	-
822	2	18	2	14	-	-
822	2	18	1	12	-	-
822	2	18	2	12	-	-
822	2	18	3	12	-	-
822	3	18	-	-	-	-
822	3	18	1	16	-	-
822	3	18	2	16	-	-
822	3	18	3	16	-	-
822	3	18	1	14	-	-
822	3	18	1	12	-	-
822	4	18	-	-	-	-
822	4	18	1	16	-	-
822	4	18	2	16	-	-
822	4	18	1	12	-	-
822	5	18	-	-	-	-
822	5	18	1	12	-	-
822	6	18	-	-	-	-
822	1	16	2	14	-	-
822	1	16	3	14	-	-
822	1	16	4	14	-	-
822	1	16	2	12	-	-
822	1	16	3	12	-	-
822	1	16	4	12	-	-
822	1	16	2	10	-	-
822	2	16	-	-	-	-
822	2	16	1	14	-	-
822	2	16	2	14	-	-
822	2	16	3	14	-	-
822	2	16	1	12	-	-
822	2	16	2	12	-	-
822	2	16	3	12	-	-
822	2	16	1	10	-	-
822	2	16	2	10	-	-
822	2	16	1	8	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
822	3	16	-	-	-	-
822	3	16	1	14	-	-
822	3	16	1	12	-	-
822	3	16	2	12	-	-
822	3	16	1	8	-	-
822	4	16	-	-	-	-
822	4	16	1	14	-	-
822	4	16	1	12	-	-
822	4	16	1	8	-	-
822	5	16	-	-	-	-
822	1	14	2	12	-	-
822	1	14	3	12	-	-
822	1	14	4	12	-	-
822	1	14	2	10	-	-
822	2	14	-	-	-	-
822	2	14	1	12	-	-
822	2	14	2	12	-	-
822	2	14	3	12	-	-
822	2	14	1	10	-	-
822	2	14	2	10	-	-
822	2	14	1	8	-	-
822	3	14	-	-	-	-
822	3	14	1	12	-	-
822	3	14	2	12	-	-
822	3	14	1	10	-	-
822	3	14	1	8	-	-
822	4	14	-	-	-	-
822	4	14	1	12	-	-
822	4	14	1	10	-	-
822	5	14	1	10	-	-
822	1	12	2	10	-	-
822	2	12	-	-	-	-
822	2	12	1	10	-	-
822	2	12	1	8	-	-
822	3	12	-	-	-	-
822	3	12	1	10	-	-
822	4	12	-	-	-	-
822	5	12	-	-	-	-
822	2	10	-	-	-	-
822	3	10	-	-	-	-
822	2	8	-	-	-	-
833	1	22	2	20	-	-
833	1	22	3	20	-	-
833	1	22	4	20	-	-
833	1	22	2	18	-	-
833	1	22	3	18	-	-
833	1	22	4	18	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
833	2	22	1	20	-	-
833	2	22	2	20	-	-
833	2	22	3	20	-	-
833	2	22	1	18	-	-
833	2	22	2	18	-	-
833	2	22	3	18	-	-
833	2	22	1	16	-	-
833	2	22	2	16	-	-
833	2	22	3	16	-	-
833	3	22	1	20	-	-
833	3	22	2	20	-	-
833	3	22	1	18	-	-
833	3	22	2	18	-	-
833	3	22	1	16	-	-
833	4	22	-	-	-	-
833	4	22	1	20	-	-
833	4	22	1	18	-	-
833	4	22	1	16	-	-
833	5	22	-	-	-	-
833	1	20	2	18	-	-
833	1	20	3	18	-	-
833	1	20	4	18	-	-
833	2	20	1	18	-	-
833	2	20	2	18	-	-
833	2	20	3	18	-	-
833	2	20	1	16	-	-
833	2	20	2	16	-	-
833	2	20	3	16	-	-
833	3	20	-	-	-	-
833	3	20	1	18	-	-
833	3	20	2	18	-	-
833	3	20	1	16	-	-
833	4	20	-	-	-	-
833	4	20	1	18	-	-
833	4	20	1	16	-	-
833	5	20	-	-	-	-
833	1	18	1	16	-	-
833	1	18	2	16	-	-
833	1	18	3	16	-	-
833	1	18	4	16	-	-
833	1	18	5	16	-	-
833	1	18	2	14	-	-
833	1	18	1	12	-	-
833	1	18	2	12	-	-
833	1	18	3	12	-	-
833	2	18	-	-	-	-
833	2	18	1	16	-	-
833	2	18	2	16	-	-
833	2	18	1	12	-	-
833	2	18	2	12	-	-
833	2	18	1	8	-	-
833	2	18	1	16	-	-
833	2	18	2	16	-	-
833	2	18	3	16	-	-
833	2	18	4	16	-	-
833	2	18	5	16	-	-
833	2	18	1	14	-	-
833	2	18	2	14	-	-
833	2	18	3	14	-	-
833	2	18	4	14	-	-
833	2	18	5	14	-	-
833	2	18	6	14	-	-
833	2	18	7	14	-	-
833	2	18	8	14	-	-
833	2	18	9	14	-	-
833	2	18	10	14	-	-
833	2	18	11	14	-	-
833	2	18	12	14	-	-
833	2	18	13	14	-	-
833	2	18	14	14	-	-
833	2	18	15	14	-	-
833	2	18	16	14	-	-
833	2	18	17	14	-	-
833	2	18	18	14	-	-
833	2	18	19	14	-	-
833	2	18	20	14	-	-
833	2	18	21	14	-	-
833	2	18	22	14	-	-
833	2	18	23	14	-	-
833	2	18	24	14	-	-
833	2	18	25	14	-	-
833	2	18	26	14	-	-
833	2	18	27	14	-	-
833	2	18	28	14	-	-
833	2	18	29	14	-	-
833	2	18	30	14	-	-
833	2	18	31	14	-	-
833	2	18	32	14	-	-
833	2	18	33	14	-	-
833	2	18	34	14	-	-
833	2	18	35	14	-	-
833	2	18	36	14	-	-
833	2	18	37	14	-	-
833	2	18	38	14	-	-
833	2	18	39	14	-	-
833	2	18	40	14	-	-
833	2	18	41	14	-	-
833	2	18	42	14	-	-
833	2	18	43	14	-	-
833	2	18	44	14	-	-
833	2	18	45	14	-	-
833	2	18	46	14	-	-
833	2	18	47	14	-	-
833	2	18	48	14	-	-
833	2	18	49	14	-	-
833	2	18	50	14	-	-
833	2	18	51	14	-	-
833	2	18	52	14	-	-
833	2	18	53	14	-	-
833	2	18	54	14	-	-
833	2	18	55	14	-	-
833	2	18	56	14	-	-
833	2	18	57	14	-	-
833	2	18	58	14	-	-
833	2	18	59	14	-	-
833	2	18	60	14	-	-
833	2	18	61	14	-	-
833	2	18	62	14	-	-
833	2	18	63	14	-	-
833	2	18	64	14	-	-
833	2	18	65	14	-	-
833	2	18	66	14	-	-
833	2	18	67	14	-	-
833	2	18	68	14	-	-
833	2	18	69	14	-	-
833	2	18	70	14	-	-
833	2	18	71	14	-	-
833	2	18	72	14	-	-
833	2	18	73	14	-	-
833	2	18	74	14	-	-
833	2	18	75	14	-	-
833	2	18	76	14	-	-
833	2	18	77	14	-	-
833	2	18	78	14	-	-
833	2	18	79	14	-	-
833	2	18	80	14	-	-
833	2	18	81	14	-	-
833	2	18	82	14	-	-
833	2	18	83	14	-	-
833	2	18	84	14	-	-
833	2	18	85	14	-	-
833	2	18	86	14	-	-
833	2	18	87	14	-	-
833	2	18	88	14	-	-
833	2	18	89	14	-	-
833	2	18	90	14	-	-
833	2	18	91	14	-	-
833	2	18	92	14	-	-
833	2	18	93	14	-	-
833	2	18	94	14	-	-
833	2	18	95	14	-	-
833	2	18	96	14	-	-
833	2	18	97	14	-	-
833	2	18	98	14	-	-
833	2	18	99	14	-	-
833	2	18	100	14	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
833	2	18	3	16	-	-
833	2	18	4	16	-	-
833	2	18	1	14	-	-
833	2	18	2	14	-	-
833	2	18	1	12	-	-
833	2	18	2	12	-	-
833	2	18	3	12	-	-
833	3	18	-	-	-	-
833	3	18	1	16	-	-
833	3	18	2	16	-	-
833	3	18	3	16	-	-
833	3	18	1	14	-	-
833	3	18	1	12	-	-
833	4	18	-	-	-	-
833	4	18	1	16	-	-
833	4	18	2	16	-	-
833	4	18	1	12	-	-
833	5	18	-	-	-	-
833	5	18	1	12	-	-
833	6	18	-	-	-	-
833	1	16	2	14	-	-
833	1	16	3	14	-	-
833	1	16	4	14	-	-
833	1	16	2	12	-	-
833	1	16	3	12	-	-
833	1	16	4	12	-	-
833	1	16	2	10	-	-
833	2	16	-	-	-	-
833	2	16	1	14	-	-
833	2	16	2	14	-	-
833	2	16	3	14	-	-
833	2	16	1	12	-	-
833	2	16	2	12	-	-
833	2	16	3	12	-	-
833	2	16	1	10	-	-
833	2	16	2	10	-	-
833	2	16	1	8	-	-
833	3	16	-	-	-	-
833	3	16	1	14	-	-
833	3	16	2	14	-	-
833	3	16	1	12	-	-
833	3	16	2	12	-	-
833	3	16	1	8	-	-
833	4	16	-	-	-	-
833	4	16	1	14	-	-
833	4	16	1	12	-	-
833	4	16	1	8	-	-
833	5	16	-	-	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
833	1	14	2	12	-	-
833	1	14	3	12	-	-
833	1	14	4	12	-	-
833	1	14	2	10	-	-
833	2	14	-	-	-	-
833	2	14	1	12	-	-
833	2	14	2	12	-	-
833	2	14	3	12	-	-
833	2	14	1	10	-	-
833	2	14	2	10	-	-
833	2	14	1	8	-	-
833	3	14	-	-	-	-
833	3	14	1	12	-	-
833	3	14	2	12	-	-
833	3	14	1	10	-	-
833	3	14	1	8	-	-
833	4	14	-	-	-	-
833	4	14	1	12	-	-
833	4	14	1	10	-	-
833	5	14	-	-	-	-
833	1	12	2	10	-	-
833	2	12	-	-	-	-
833	2	12	1	10	-	-
833	2	12	1	8	-	-
833	3	12	-	-	-	-
833	3	12	1	10	-	-
833	4	12	-	-	-	-
833	2	10	-	-	-	-
833	3	10	-	-	-	-
Cuivre-cuivre						
933	1	22	1	20	-	-
933	1	22	2	20	-	-
933	1	22	3	20	-	-
933	1	22	4	20	-	-
933	1	22	5	20	-	-
933	1	22	1	18	-	-
933	1	22	2	18	-	-
933	1	22	3	18	-	-
933	1	22	4	18	-	-
933	1	22	5	18	-	-
933	1	22	1	16	-	-
933	1	22	2	16	-	-
933	1	22	3	16	-	-
933	1	22	4	16	-	-
933	1	22	5	16	-	-
933	2	22	1	20	-	-
933	2	22	2	20	-	-
933	2	22	3	20	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
933	2	22	4	20	-	-
933	2	22	1	18	-	-
933	2	22	2	18	-	-
933	2	22	3	18	-	-
933	2	22	4	18	-	-
933	2	22	1	16	-	-
933	2	22	2	16	-	-
933	2	22	3	16	-	-
933	2	22	4	16	-	-
933	3	22	1	20	-	-
933	3	22	2	20	-	-
933	3	22	3	20	-	-
933	3	22	1	18	-	-
933	3	22	2	18	-	-
933	3	22	3	18	-	-
933	3	22	4	18	-	-
933	3	22	1	16	-	-
933	3	22	2	16	-	-
933	3	22	3	16	-	-
933	3	22	4	16	-	-
933	4	22	1	20	-	-
933	4	22	2	20	-	-
933	4	22	1	18	-	-
933	4	22	2	18	-	-
933	4	22	1	16	-	-
933	4	22	2	16	-	-
933	4	22	-	-	-	-
933	5	22 Sol.	-	-	-	-
933	6	22 Sol.	-	-	-	-
933	1	20	1	18	-	-
933	1	20	2	18	-	-
933	1	20	3	18	-	-
933	1	20	4	18	-	-
933	1	20	1	16	-	-
933	1	20	2	16	-	-
933	1	20	3	16	-	-
933	1	20	4	16	-	-
933	1	20	1	14	-	-
933	1	20	2	14	-	-
933	1	20	3	14	-	-
933	1	20	4	14	-	-
933	2	20	1	18	-	-
933	2	20	2	18	-	-
933	2	20	3	18	-	-
933	2	20	1	16	-	-
933	2	20	2	16	-	-
933	2	20	3	16	-	-
933	2	20	1	14	-	-
933	2	20	2	14	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
933	2	20	2	14	-	-
933	2	20	2	14	-	-
933	2	20	3	14	-	-
933	2	20	-	-	-	-
933	3	20	1	18	-	-
933	3	20	2	18	-	-
933	3	20	1	16	-	-
933	3	20	2	16	-	-
933	3	20	1	14	-	-
933	3	20	2	14	-	-
933	3	20	-	-	-	-
933	4	20	1	18	-	-
933	4	20	2	18	-	-
933	4	20	1	16	-	-
933	4	20	2	16	-	-
933	4	20	1	14	-	-
933	4	20	2	14	-	-
933	4	20	-	-	-	-
933	5	20 Sol.	-	-	-	-
933	6	20 Sol.	-	-	-	-
933	1	18	1	16	-	-
933	1	18	2	16	-	-
933	1	18	3	16	-	-
933	1	18	4	16	-	-
933	1	18	5	16	-	-
933	1	18	1	14	-	-
933	1	18	2	14	-	-
933	1	18	3	14	-	-
933	1	18	4	14	-	-
933	1	18	1	12	-	-
933	1	18	2	12	-	-
933	1	18	3	12	-	-
933	1	18	4	12	-	-
933	1	18	1	10	-	-
933	1	18	2	10	-	-
933	2	18	1	16	-	-
933	2	18	2	16	-	-
933	2	18	3	16	-	-
933	2	18	4	16	-	-
933	2	18	1	14	-	-
933	2	18	2	14	-	-
933	2	18	3	14	-	-
933	2	18	4	14	-	-
933	2	18	1	12	-	-
933	2	18	2	12	-	-
933	2	18	3	12	-	-
933	2	18	1	10	-	-
933	2	18	2	10	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
933	2	18	-	-	-	-
933	3	18	1	16	-	-
933	3	18	2	16	-	-
933	3	18	3	16	-	-
933	3	18	1	14	-	-
933	3	18	2	14	-	-
933	3	18	3	14	-	-
933	3	18	1	12	-	-
933	3	18	2	12	-	-
933	3	18	3	12	-	-
933	3	18	1	10	-	-
933	3	18	2	10	-	-
933	3	18	-	-	-	-
933	4	18	1	16	-	-
933	4	18	2	16	-	-
933	4	18	1	14	-	-
933	4	18	2	14	-	-
933	4	18	1	12	-	-
933	4	18	2	12	-	-
933	4	18	1	10	-	-
933	4	18	-	-	-	-
933	5	18	1	16	-	-
933	5	18	1	14	-	-
933	5	18	1	12	-	-
933	5	18	-	-	-	-
933	6	18	-	-	-	-
933	1	16	1	14	-	-
933	1	16	1	14	-	-
933	1	16	1	14	-	-
933	1	16	2	14	-	-
933	1	16	2	14	-	-
933	1	16	2	14	-	-
933	1	16	3	14	-	-
933	1	16	4	14	-	-
933	1	16	1	12	-	-
933	1	16	1	12	-	-
933	1	16	2	12	-	-
933	1	16	3	12	-	-
933	1	16	4	12	-	-
933	1	16	1	10	-	-
933	1	16	2	10	-	-
933	2	16	1	14	-	-
933	2	16	1	14	-	-
933	2	16	2	14	-	-
933	2	16	2	14	-	-
933	2	16	2	14	-	-
933	2	16	3	14	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
933	2	16	4	14	-	-
933	2	16	1	12	-	-
933	2	16	1	12	-	-
933	2	16	2	12	-	-
933	2	16	3	12	-	-
933	2	16	1	10	-	-
933	2	16	2	10	-	-
933	2	16	1	8 Strd.	-	-
933	2	16	-	-	-	-
933	3	16	1	14	-	-
933	3	16	1	14	-	-
933	3	16	1	14	-	-
933	3	16	2	14	-	-
933	3	16	3	14	-	-
933	3	16	1	12	-	-
933	3	16	2	12	-	-
933	3	16	1	10	-	-
933	3	16	2	10	-	-
933	3	16	1	8 Strd.	-	-
933	3	16	-	-	-	-
933	4	16	1	14	-	-
933	4	16	2	14	-	-
933	4	16	1	12	-	-
933	4	16	1	12	-	-
933	4	16	2	12	-	-
933	4	16	1	10	-	-
933	4	16	1	8 Strd.	-	-
933	4	16	-	-	-	-
933	5	16	1	14	-	-
933	5	16	1	10	-	-
933	5	16	-	-	-	-
933	6	16	-	-	-	-
933	1	14	1	12	-	-
933	1	14	1	12	-	-
933	1	14	2	12	-	-
933	1	14	2	12	-	-
933	1	14	3	12	-	-
933	1	14	4	12	-	-
933	1	14	1	10	-	-
933	1	14	2	10	-	-
933	1	14	1	8 Strd.	-	-
933	1	14	-	-	-	-
933	2	14	1	12	-	-
933	2	14	1	12	-	-
933	2	14	2	12	-	-
933	2	14	3	12	-	-
933	2	14	1	10	-	-

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
933	2	14	1	8 Strd.	-	-
933	2	14	-	-	-	-
933	3	14	1	12	-	-
933	3	14	2	12	-	-
933	3	14	1	10	-	-
933	3	14	1	8 Strd.	-	-
933	3	14	-	-	-	-
933	4	14	1	12	-	-
933	4	14	1	10	-	-
933	4	14	-	-	-	-
933	5	14	-	-	-	-
933	1	12	1	10	-	-
933	1	12	2	10	-	-
933	1	12	1	8 Strd.	-	-
933	1	12	-	-	-	-
933	2	12	1	10	-	-
933	2	12	1	8 Strd.	-	-
933	2	12	-	-	-	-
933	3	12	1	10	-	-
933	3	12	-	-	-	-
933	4	12	-	-	-	-
933	1	10	1	8 Strd.	-	-
933	1	10	-	-	-	-
933	2	10	-	-	-	-
933	3	10	-	-	-	-
WP33	2	20	-	-	-	-
WP33	1	18	1	16	-	-
WP33	1	18	2	16	-	-
WP33	1	18	3	16	-	-
WP33	1	18	1	14	-	-
WP33	1	18	2	14	-	-
WP33	1	18	3	14	-	-
WP33	2	18	-	-	-	-
WP33	2	18	1	16	-	-
WP33	2	18	2	16	-	-
WP33	2	18	3	16	-	-
WP33	2	18	1	14	-	-
WP33	2	18	2	14	-	-
WP33	3	18	-	-	-	-
WP33	4	18	-	-	-	-
WP33	2	16	-	-	-	-
WP33	3	16	-	-	-	-
WP33	4	16	-	-	-	-
WP33	1	14	1	18	-	-
WP33	1	14	2	18	-	-
WP33	1	14	3	18	-	-

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
WP33	1	14	4	18	-	-
WP33	1	14	1	16	-	-
WP33	1	14	1	16	1	20
WP33	1	14	1	16	2	20
WP33	1	14	1	16	3	20
WP33	1	14	1	16	4	20
WP33	1	14	1	16	1	18
WP33	1	14	1	16	2	18
WP33	1	14	1	16	3	18
WP33	1	14	2	16	-	-
WP33	1	14	3	16	-	-
WP33	2	14	-	-	-	-
WP33	2	14	1	18	1	20
WP33	2	14	1	18	2	20
WP33	2	14	1	18	3	20
WP33	2	14	1	16	-	-
WP33	2	14	1	16	1	20
WP33	2	14	1	16	2	20
WP33	2	14	1	16	3	20
WP33	2	14	1	16	1	18
WP33	2	14	1	16	2	18
WP33	2	14	1	16	3	18
WP33	2	14	2	16	-	-
WP33	3	14	-	-	-	-
WP33	3	14	1	18	1	20
WP33	3	14	1	18	2	20
WP33	3	14	1	16	1	20
WP33	3	14	1	16	2	20
WP33	3	14	1	16	1	18
WP33	3	14	1	16	2	18
WP33	1	12	-	-	-	-
WP33	1	12	3	18	-	-
WP33	1	12	4	18	-	-
WP33	1	12	1	16	1	20
WP33	1	12	1	16	2	20
WP33	1	12	1	16	3	20
WP33	1	12	1	16	4	20
WP33	1	12	1	16	1	18
WP33	1	12	1	16	2	18
WP33	1	12	1	16	3	18
WP33	1	12	1	16	4	18
WP33	1	12	2	16	-	-
WP33	1	12	3	16	-	-
WP33	1	12	1	14	-	-
WP33	1	12	1	14	1	20
WP33	1	12	1	14	2	20

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
WP33	1	12	1	14	3	20
WP33	1	12	1	14	4	20
WP33	1	12	1	14	1	18
WP33	1	12	1	14	2	18
WP33	1	12	1	14	3	18
WP33	1	12	1	14	1	16
WP33	1	12	1	14	2	16
WP33	1	12	1	14	3	16
WP33	1	12	2	14	-	-
WP33	1	12	2	14	1	16
WP33	2	12	-	-	-	-
WP33	2	12	1	18	-	-
WP33	2	12	2	18	-	-
WP33	2	12	1	16	-	-
WP33	2	12	1	16	1	20
WP33	2	12	1	16	2	20
WP33	2	12	1	16	3	20
WP33	2	12	1	16	1	18
WP33	2	12	1	16	2	18
WP33	2	12	1	14	-	-
WP33	2	12	1	14	1	20
WP33	2	12	1	14	2	20
WP33	2	12	1	14	1	18
WP33	3	12	-	-	-	-
WP33	1	10	1	18	-	-
WP33	1	10	2	18	-	-
WP33	1	10	1	16	-	-
WP33	1	10	2	16	-	-
WP33	1	10	3	16	-	-
WP33	1	10	1	14	1	20
WP33	1	10	1	14	2	20
WP33	1	10	1	14	3	20
WP33	1	10	1	14	1	18
WP33	1	10	1	14	2	18
WP33	1	10	1	14	-	-
WP33	1	10	1	14	1	16
WP33	1	10	2	14	-	-
WP33	1	10	1	12	-	-
WP33	1	10	1	12	1	18
WP33	1	12	-	-	-	-
WP33	2	12	-	-	-	-
WP33	3	12	-	-	-	-
WP39	3	16	-	-	-	-
WP39	4	16	-	-	-	-
WP39	5	16	-	-	-	-
WP39	1	14	1	16	2	20
WP39	1	14	1	16	3	20

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
WP39	1	14	1	16	4	20
WP39	1	14	1	16	1	18
WP39	1	14	1	16	2	18
WP39	1	14	1	16	3	18
WP39	2	14	-	-	-	-
WP39	2	14	1	18	1	20
WP39	2	14	1	18	2	20
WP39	2	14	1	18	3	20
WP39	2	14	2	18	-	-
WP39	2	14	3	18	-	-
WP39	2	14	4	18	-	-
WP39	2	14	1	16	1	20
WP39	2	14	1	16	2	20
WP39	2	14	1	16	3	20
WP39	2	14	1	16	1	18
WP39	2	14	1	16	2	18
WP39	2	14	1	16	3	18
WP39	2	14	2	16	-	-
WP39	2	14	3	16	-	-
WP39	3	14	-	-	-	-
WP39	3	14	1	18	1	20
WP39	3	14	1	18	2	20
WP39	3	14	1	16		
WP39	3	14	1	16	1	20
WP39	3	14	1	16	2	20
WP39	3	14	1	16	1	18
WP39	3	14	1	16	2	18
WP39	3	14	2	16	-	-
WP39	3	14	1	12	-	-
WP39	4	14	-	-	-	-
WP39	5	14	-	-	-	-
WP39	1	12	3	18	-	-
WP39	1	12	4	18	-	-
WP39	1	12	1	16	2	20
WP39	1	12	1	16	3	20
WP39	1	12	1	16	4	20
WP39	1	12	1	16	1	18
WP39	1	12	1	16	2	18
WP39	1	12	1	16	3	18
WP39	1	12	1	16	4	18
WP39	1	12	2	16	-	-
WP39	1	12	3	16	-	-
WP39	1	12	4	16	-	-
WP39	1	12	1	14	1	20
WP39	1	12	1	14	2	20
WP39	1	12	1	14	3	20

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
WP39	1	12	1	14	4	20
WP39	1	12	1	14	1	18
WP39	1	12	1	14	2	18
WP39	1	12	1	14	3	18
WP39	1	12	1	14	4	18
WP39	1	12	1	14	1	16
WP39	1	12	1	14	2	16
WP39	1	12	1	14	3	16
WP39	1	12	2	14	1	16
WP39	1	12	2	14	2	16
WP39	1	12	2	14	3	16
WP39	2	12	-	-	-	-
WP39	2	12	1	16	1	20
WP39	2	12	1	16	2	20
WP39	2	12	1	16	3	20
WP39	2	12	1	16	1	18
WP39	2	12	1	16	2	18
WP39	2	12	1	16	3	18
WP39	2	12	3	16		
WP39	2	12	1	14	1	20
WP39	2	12	1	14	2	20
WP39	2	12	1	14	3	20
WP39	2	12	1	14	1	18
WP39	2	12	1	14	2	18
WP39	2	12	1	14	3	18
WP39	2	12	1	14	1	16
WP39	2	12	1	14	2	16
WP39	2	12	1	14	3	16
WP39	2	12	2	14	-	-
WP39	2	12	2	14	1	16
WP39	3	12	-	-	-	-
WP39	4	12	-	-	-	-
WP39	1	10	1	18	-	-
WP39	1	10	2	18	-	-
WP39	1	10	3	16	-	-
WP39	1	10	1	14	-	-
WP39	1	10	1	14	2	20
WP39	1	10	1	14	3	20
WP39	1	10	1	14	4	20
WP39	1	10	1	14	2	18
WP39	1	10	1	14	3	18
WP39	1	10	1	14	4	18
WP39	1	10	1	14	1	16
WP39	1	10	1	14	2	16
WP39	1	10	1	14	3	16

Guide de référence - Combinaisons de fils

N° de modèle	Nbre de cond.	AWG	Nbre de cond.	AWG	Nbre de cond.	AWG
WP39	1	10	1	14	4	16
WP39	1	10	2	14	-	-
WP39	1	10	3	14	-	-
WP39	1	10	1	12	-	-
WP39	1	10	1	12	2	18
WP39	1	10	1	12	3	18
WP39	1	10	1	12	4	18
WP39	1	10	1	12	1	16
WP39	1	10	1	12	2	16
WP39	1	10	1	12	3	16
WP39	1	10	1	12	4	16
WP39	1	10	1	12	1	14
WP39	1	10	1	12	2	14
WP39	1	10	2	12	-	-
WP39	1	10	3	12	-	-
WP39	2	10	-	-	-	-
WP39	2	10	1	14	-	-
WP39	2	10	2	14	-	-
WP39	2	10	1	12	-	-
WP39	3	10	-	-	-	-
WP39	4	10	-	-	-	-
WP39	1	8	-	-	-	-
WP39	2	8	-	-	-	-